


JENA 6


design: Roberto Mantovani

Supply current
 Courant d'alimentation
 Corriente de alimentación
500mA (V_f 8.7V)


Power
 Pouissance
 Potencia
4.5W



Photometric diagrams



| CCT | Flux | CRI |
|-------|--------|-----|
| 2700K | 540 lm | 98+ |
| 3000K | 600 lm | 98+ |
| 3500K | 610 lm | 98+ |
| 4000K | 620 lm | 98+ |



Code Construction

Construction du code produit
 Construcción del código de producto

XJ21 | X | XX | X | E


| XJ21 | X | Beam angle | XX | Color Temp. | X | Finishing | E |
|------|---|-------------------------------------|----|---|---|--|---|
| | | Angle de faisceau Ángulo del haz | | Température couleur Temperatura de color | | Finitions Acabados | |
| | 1 | 25° | 27 | 2700K | G | Grey Gris | |
| | 2 | 45° | 30 | 3000K | N | Black Noir Negro | |
| | | | 35 | 3500K | K | COR-TEN | |
| | | | 40 | 4000K | Z | INOX AISI 316L Steel Acier Acero | |
| | | | CU | Custom | | | |

Drivers

Alimentateurs
 Alimentadores

Series wiring

Câblage en série
 Cableado en serie



0-10V

FLEXA-60-PRO-CC-10V

Programmable 60W CC 0-10V Dimming
 Dimming Range: 0.1%
Min. 1/Max. 6 Fixtures per Driver

Phase

FLEXA-12-500-CC-ELV

12W 500mA Constant Current
 Dimming Range: 10%
Min. 1/Max. 2 Fixtures per Driver

FLEXA-23-500-CC-ELV

23W 500mA Constant Current
 Dimming Range: 10%
Min. 3/Max. 5 Fixtures per Driver

Lutron 2-Wire Phase

Hi-Lume 2-Wire Phase / 500mA Constant Current / Dimming Range: 1%

LTEA.1

Min. 1/Max. 2
 Fixtures per Driver

LTEA.2

Min. 2/Max. 4
 Fixtures per Driver

LTEA.3

Min. 4/Max. 6
 Fixtures per Driver

Lutron Ecosystem

LDE.1

Hi-Lume Ecosystem
 500mA Constant Current
 Dimming Range: 1%
Min. 2/Max. 3 Fixtures per Driver


LDE.2

Hi-Lume Ecosystem Premier
 500mA Constant Current
 Dimming Range: 1%
Min. 4/Max. 5 Fixtures per Driver

Optionals - Accessoires - Accesorios


CSXJ02

Recessing box
 Boîtier d'encastrement
 Caja de empotrar



CSXJ02-RAB

Recessing box + RAB Housing



L001

Low luminance louvre
 Filtre basse luminance
 Filtro de baja luminancia



Note: the filter must be ordered together with the lighting fixture
Note: le filtre doit être commandé en même temps que l'appareil
Nota: el filtro debe pedirse junto con la luminaria